

DEVICE

The Lansen door and window device alerts as soon as a door or window is opened or closed thanks to its internal onboard reed relay. The functionality can be increased further by adding an external reed relay and magnet to monitor, for example, another window.

Much care have been taken to design a sleek, good looking device with high security and performance. The design allows for discrete integration when in home environment.

PERFORMANCE

The device has a robust design with tamper detection if opened or removed from the wall. A message is sent if sabotage is detected or restored. This status is transmitted in every packet. The battery level is continuously monitored and a low level warning is issued when battery is nearing depletion.

FIRMWARE

MODES	Configurable C, T or S
INTERVAL	Configurable 60s - 1 hour
ENCRYPTION	AES128 encryption OMS mode 5, Profile A. Configurable ON/OFF, and KEY
STANDARD	T1-Mode, 90 seconds, encryption ON.

WARNINGS

TAMPER DETECTION	Product opened or removed from the wall
BATTERY	Low battery

POWER/LIFETIME

POWER SUPPLY	3.6V Li-SOCI2, AA battery
VOLTAGE	2.4 to 3.6V
LIFESPAN	14 years typical, depending on configuration and operating temperature.
RADIO	14 dBm output power to antenna

GENERAL INFORMATION

STANDARDS	2014/53/EU (RED) EN 13757-3/4:2013, OMS 4.0.2
TEMPERATURE	-40° to +85°
RELATIVE HUMIDITY.	None condensing
COLOR	White
SIZE (W x H x D)	25.5 x 105 x 22 mm
MATERIAL	ABS

DEVICES

LAN-WMBUS-M2	Door and window device
--------------	------------------------

ACCESSORIES

LAN-EXT-MAG-A	External cable connected reed relay
LAN-CF-CABLE	USB Configuration cable

MEASUREMENTS

The total number of openings and current opening status is sent periodically using the Wireless MBUS protocol. This makes the sensor ideal for integration in data collecting systems, for energy management and HVAC-control.

The data from the device could also be protected using the AES128 encryption compliant with OMS standard.

EXTERNAL REED RELAY WITH MAGNET

An external reed relay can be connected to the device so that another window or door can be monitored. In other words, by adding an external reed relay, up to two windows/doors can be monitored and the device will alert if one of them are opened.

CONFIGURATION

The MBUS mode, transmission interval and encryption can be configured using a USB configuration cable connected to a PC.

